



IN200 *EVOLUTION*

INTEGRATED AMPLIFIER-PREAMPLIFIER.

Reworked power supplies, improved audio performance, new speaker terminals...

- 8 mm brushed, micro-blasted and anodized aluminum front panel, high-precision engraving.
- 1.5 mm steel chassis.
- Two 340 VA toroidal transformers for the audio stages plus 10 VA for the digital stages.
- High-quality and shielded MKP link capacitors.
- Bipolar transistor and LED current sources to ensure perfect voltage stability.
- New tellurium copper speaker outputs.
- Possibility to choose the standby mode: Low consumption or preheating.
- Precise balance adjustment, possibility to memorize it.
- Possibility to rename the inputs.
- High-contrast OLED display (on or off mode after 5 seconds of inactivity).
- ATOLL global remote control supplied as standard.
- The IN200 EVO is compatible with the DA100 and DA200 boards (optional).



CONNECTIVITY

5 Line Inputs: AUX or PHONO (optional), CD, TUNER, DVD, TAPE.

1 By-pass Input.

1 12V Trigger Output.

Possibility of adding the DA100 and DA200 digital boards (optional):

DA100

- 2 Optical Inputs.
- 2 Coaxial Inputs.

DA200

- 2 Optical Inputs.
- 2 Coaxial Inputs.
- 1 Asynchronous USB & DSD Input.
- 1 Bluetooth Input.

TECHNICAL DATA

Power in Wrms/channel/8Ω (230v):	120 W
Power in Wrms/channel/4Ω (230v):	200 W
Power supply:	2×340 VA + 10 VA
Total of capacitors:	59 220 μF
Number of inputs:	5+1 BY-PASS
Power consumption with switch off:	0 W
Power consumption in standby (low consumption):	<0,5 W
Power consumption in preheating mode:	18 W
Power consumption in operation:	19 W - 600 W
Input impedance:	220 kΩ
Maximum input level:	3,5 Vrms
Sensitivity:	350 mV
Signal/noise ratio:	100 dB
Distortion at 1 kHz:	0,05% / (10 W)
Bandwidth:	5 Hz - 100 kHz
Rise time:	2,5 μs
Dimensions:	440×309×95 mm
Weight:	12 Kg

ATOLL
ELECTRONIQUE

High Fidelity Material
designed and manufactured in France

MADE IN FRANCE